Fujikura

August 17, 2010

No. V-8363A

Messrs.

SPECIFICATIONS

Oxygen sensor

Model: FCX - UC

RoHS compliance model, Ceramic base.

Project:

Reference:

Fujikura Ltd.

Specifications of Oxygen Sensor Unit **V-8363A**

1. General:

This document describes the customized specifications of a ceramic oxygen sensor unit, FUJIKURA FCX-UC.

Table shown below is revision records of this specification

V				
IV				
III				
II				
I	Aug.17th,2010	M. Hashimoto	Revised the marking format	(A)
Est.	11-30-2006	H. Nishida		
	Date	Name	Comments	Remark

Model	FCX-UC (RoHS compliance model, Ceramic base)
1. Measuring Gas	Oxygen
2. Measurement Method	Limiting current method using Zirconia Solid-Electrolyte
3. Dimension and weight	Please see the drawing 9-760-001, Approx. 7g
4. Measurement Range	0.1 to 25 %O_2
5. Output current (IL)	60 ~ 80uA
	in free air , 1.3V sensing voltage (Vs), 1.5W heating
	Theoretical output is given by following equation.
	$\mathbf{I_L = -\ (\ [A]\ /\ 0.2357\ ) \times \ln\ (\ 1 - [O_2\%]\ /\ 100\ )}$ **-----(1)**
	[A] = Output current in 21.0% O_2 (uA)
	[O_2%] = Oxygen concentration (vol.%)
6. Accuracy	within +/- 0.5%O_2
7. Response Time	within 30 sec. (90% value)
8. Life time	3 years in free air, continuous Vs
9. Heater	Power consumption: 1.5WDC +/- 5%
	Voltage(Vh) for 1.5W: 1.7~3.0VDC (individual for each sensor)
	Warm up rate: Maximum 40mV/sec
10. Sensing element	Recommended Vs=1.3V for free air
11. Operating temperature	-10 ~ 50 degC
12. Storage temperature	-40 ~ 120 degC
13. Humidity	0 ~ 85 RH … Without condensation
14. Ambient pressure	0.5 ~ 5 atm

15. Vibration resistance	JIS C 5025 class A Maximum 9G
16. Warranty	Within one year after shipment For further information, please feel free to contact us.

Output current of FCX-UC

	1	2	3	4	5	10	15	20	25	%O2
min	2.6	5.1	7.8	10.4	13.1	26.8	41.4	56.8	73.2	uA
max	3.4	6.9	10.3	13.9	17.4	35.8	55.2	75.7	97.6	uA

Marking

UC: FCX-UC

Ex. C8N001 : Year(2006), Month(August), serial number 001.

1st digit number (or alphabet) shows YEAR -------- *** Remark (A)**

Examples;

2008->A	**2018->8,**	**2028->A,**	**2038->8**
2009->B,	**2019->9,**	**2029->B,**	**2039->9**
2010->C,	**2020->0,**	**2030->C,**	**2040->0**
2011->D,	**2021->1,**	**2031->D,**	**-**
2012->E,	**2022->2,**	**2032->E**	*** 20 years cycle.**
2013->F,	**2023->3,**	**2033->F**	
2014->G,	**2024->4,**	**2034->G,**	
2015->H,	**2025->5,**	**2035->H**	
2016->I,	**2026->6,**	**2036->I**	
2017->J,	**2027->7,**	**2037->J**	

2nd digit number (or alphabet) shows Month

Ex. Jan.->1. Feb.->2, Mar.->3,,,,,,,,,Oct.->X, Nov.->Y, Dec.->Z

3rd digit alphabet is always "N"

Last three digit number shows Serial number of production.

Ex. 001, 002, ------, 999.



B 配接続図:Conection Diagram



(1) Vs (+) : センサ出力端子 (+) :Sensing terminal(+)
(2) Vs (-) : センサ出力端子 (-) :Sensing terminal(-)
(3) NC : 未使用端子 :Non-conected terminal
(4) VH (+) : ヒータ電圧端子 (+) :Heater terminal(+)
(5) VH (-) : ヒータ電圧端子 (-) :Heater terminal(-)

PART NO.	部品名 NAME OF PARTS	材質 MAT'L	個数 QTY	備考 REMARKS
4	ステム STEM	~~Plastics~~ Ceramics C	1	
3	リードピン POST PIN	Nickle	5	金メッキ Gold plating
2	リング RING	Brass	1	ニッケルメッキ Nickle plating
1	メッシュカバー MESH COVER	SUS316	1	100メッシュ 100mesh

PROJECT NAME:

MARK	変更 REVISIONS	年月日 DATE	変更者 BY
C	Sensor stem material: Plastic -> Ceramics	SEP 7,2006	H. N
B	誤記訂正(ピン配置) Correct of Mistakes(Pin arrangement)	97/11/04	永野
A	寸法見直し(インチ表示追記)	967/11/25	永野

フジクラ Fujikura Ltd. Tokyo, Japan

承認 APPROVED BY 安原
検図 CHECKED BY 澤
設計 DESIGNED BY
製図 DRAWN BY R.Nagano

第三角法 3RD ANGLE PROJECTION
単位 UNITS mm (inch)
尺度 SCALE Free
DATE OF ISSUE 1997.11.04
DATE OF DESIGN 1996.11.25

名称 TITLE
OXGEN SENSOR ELEMENT
OUTLINE DIMENSIONS
(Model: FCX-U, UW, UL, UC, UWC, ULC)

図面番号 DRAWING NO. 9-760-001
REV.MARK C

Supporting your great ideas
www.pewatron.com
PEWATRON a member of the Angst + Pfister Group

Precautions Relating to the Use of the Fujikura Oxygen Sensor

Carefully read the following before using the oxygen sensor and analyzer.

1. Applications for medical appliances, life-support equipment and low oxygen detectors

(1) Fujikura products are not designed, intended or approved for use as components of surgical or life support systems, or other applications that may cause injury or death as a result. In unapproved applications or uses where the customer implies, directly or indirectly, resultant injuries or deaths are due to Fujikura, Fujikura affiliates and agencies (citing for example, a design or manufacture fault), Fujikura, Fujikura affiliates and agencies shall be free from responsibility relating to any claims, costs, losses, and compensation.

(2) When a Fujikura product is to be used in medical appliances and oxygen detectors other than those mentioned above, it is strongly advised that fail-safe designs are established. Fujikura should be consulted for the necessary information.

2. Service life and guarantee period

(1) The end of service life shall be defined as the time when the output no longer meets the specified precision.

(2) The guarantee period is for one year from the date of shipment. During the guarantee period, should defects occur under normal conditions of use as specified in the manual and within the service life, the product will be repaired or replaced without charge. However, a repair or replacement fee will be charged in the following cases.

Defect or damage due to inappropriate transportation or handling after delivery.

Defect or damage caused by misuse, abuse or careless handling.

Defect or damage due to unauthorized repairs or changes in configuration

Damage to the cosmetic appearance caused during use

Damage from fire, earthquake, flood or other natural disasters and abnormal

Supporting your great ideas www.pewatron.com PEWATRON a member of the Angst + Pfister Group

voltage.

3. Operational precautions

3.1 Measurement of atmospheric gases

(1) Calibration gas

The sensor should be adjusted with a calibration gas that is a mixture of nitrogen, N_2 (or Argon, Ar) and oxygen, O_2. Other balance gases may result in incorrect measurements.

(2) Combustible gases

An atmosphere continuing combustible gases such as methane, alcohol, hydrogen and carbon monoxide may cause errors in measurement. Since the sensor element functions at 450°C, gases that ignite below that temperature must not be sued.

(3) Silicon gases

Never use silicon gases containing siloxane, as these gases react with the sensor and produce oxides, destroying the performance of the sensor over a very short period.

(4) Fluorocarbons

Do not use freons and others that contain halogens (F, Cl and Br), as these gasses react with materials inside the sensor and damage the performance.

(5) Sulfur oxides and hydrogen

Never use sulfur oxides (SOx) and hydrogen (H_2), as they react with the sensor and destroy the performance of the sensor over a very short period.

Supporting your great ideas www.pewatron.com PEWATRON a member of the Angst + Pfister Group

3.2 Operating conditions

(1) Dust and oil mist

Employ a filter system to eliminate dust and oil mists that clog the sensor and analyzer filter, resulting in problems, measurement errors and incorrect responses.

(2) Water and condensation moisture

Contact of the sensor with water may destroy the sensor. Exclude water from the system.

3.3 Others

(1) There is a risk to burns, since the sensor mesh is heated to 50 - 80°C while the sensor is in operation.

(2) Do not subject the sensor to a shock of 10G or greater which may cause breaks in the wiring and cracks in the sensor chip.

(3) The sensor element is made of a ceramic material. Never expose it to heat suddenly as this could destroy the element.

4. Others

Any product described in the catalogues may be altered without prior notice to improve reliability, function or design.

Fujikura is not responsible for any incidents due to application of products and circuits described in the catalogues. No Fujikura patents or rights are licensed to a third party.

Supporting your great ideas www.pewatron.com PEWATRON a member of the Angst + Pfister Group

PEWATRON
a member of the Angst + Pfister Group

We are here for you. Addresses and Contacts

Sales Switzerland

Postcode 3000 – 9999
Liechtenstein

Matthias Rüegg
Ruhbergstrasse 32
CH-9230 Flawil

Phone + 41 44 877 35 18
Mobile + 41 76 491 66 66
Fax + 41 44 877 35 19

matthias.rueegg@pewatron.com

Postcode 1000 – 2999

Raffael Favaretto
Route d'Oron 124
CH-1673 Promasens

Phone + 41 44 877 35 22
Mobile + 41 76 444 63 14
Fax + 41 44 877 35 23

raffael.favaretto@pewatron.com

Sales Germany

Postcode 60000 – 79999

Dieter Hirthe
Mühlweg 23
D-71554 Weissach i.T.

Phone + 49 719 149 60 58
Mobile + 49 163 762 74 30
Fax + 49 719 193 31 88

dieter.hirthe@pewatron.com

Postcode 10000 – 59999
Postcode 80000 – 99999

Kurt Stritzelberger
Neumarkter Str. 86a
D-81673 Munich

Phone + 49 89 260 38 47
Mobile + 49 171 803 41 35
Fax + 49 89 43 10 91 91

kurt.stritzelberger@pewatron.com

Key Accounts
Aerospace and Defence

Claus Wübbena
Vogelkamp 26
D-26655 Westerstede

Phone + 49 4488 5204 614
Mobile + 49 173 9700 691
Fax + 49 4488 5204 616

claus.wuebbena@pewatron.com

Sales Austria

Kurt Stritzelberger
Neumarkter Str. 86a
D-81673 Munich

Phone + 49 89 260 38 47
Mobile + 49 17 18 03 41 35
Fax + 49 89 43 10 91 91

kurt.stritzelberger@pewatron.com

Sales Other Countries / Product Management

Sensors

Physical Sensors
Data Acquisition

Peter Felder
Phone + 41 44 877 35 05
peter.felder@pewatron.com

Geometrical Sensors

Eric Letsch
Phone + 41 44 877 35 14
eric.letsch@pewatron.com

Power Supplies

DC-DC Converters
Switching Power Supplies
DC-AC Inverters

Sebastiano Leggio
Phone + 41 44 877 35 06
sebastiano.leggio@pewatron.com

E-Components

Current Sensors
Man Machine Interface
Measurement Probes

Sebastiano Leggio
Phone + 41 44 877 35 06
sebastiano.leggio@pewatron.com

PEWATRON AG
Thurgauerstrasse 66
CH-8052 Zurich

Phone + 41 44 877 35 00
Fax + 41 44 877 35 25

www.pewatron.com
info@pewatron.com