






		Options de transmission	Type de moteur	Tension nominale U [V]	Diamètre moteur [mm]	Couple nominal [Ncm]	Vitesse nominale [U/min]	Puissance nominale [W]
	APBR 30x50 mm	Motor only	DC brush motor	12 - 36 V	30	1	3200	3
	APBR30x60	Motor only	DC brush motor	12 - 36 V	30	1.5	3300	5
	APBR30x75	Motor only	DC brush motor	12 - 36 V	30	2	3500	7
	APBR42x70	Motor only	DC brush motor	12 - 60 V	42	3.8	3500	14
	APBR42x80	Motor only	DC brush motor	12 - 60 V	42	5.7	3100	19
	APBR42x85	Motor only	DC brush motor	12 - 60 V	42	6.5	3300	22
	APBR42x90A	Motor only	DC brush motor	12 - 60 V	42	7	3350	25
	APBR42x90B	Motor only	DC brush motor	12 - 60 V	42	10	4700	49

		Options de transmission	Type de moteur	Tension nominale U [V]	Diamètre moteur [mm]	Couple nominal [Ncm]	Vitesse nominale [U/min]	Puissance nominale [W]
	APBR42x90C	Motor only	DC brush motor	12 - 60 V	42	10	8770	92
	APBR52x95	Motor only	DC brush motor	12 - 115 V	52	10	3900	41
	APBR52x110A	Motor only	DC brush motor	12 - 115 V	52	20	3500	73
	APBR52x110B	Motor only	DC brush motor	12 - 115 V	52	20	9736	204
	APBR52x125	Motor only	DC brush motor	12 - 115 V	52	17	2800	50
	APBR54x103.5	Motor only	DC brush motor	12 - 115 V	54	18.4	3200	60
	APBR54x113	Motor only	DC brush motor	12 - 115 V	54	21.9	2580	59
	APBR54x126	Motor only	DC brush motor	12 - 115 V	54	26.1	2770	75

		Options de transmission	Type de moteur	Tension nominale U [V]	Diamètre moteur [mm]	Couple nominal [Ncm]	Vitesse nominale [U/min]	Puissance nominale [W]
	APBR54x145	Motor only	DC brush motor	12 - 115 V	54	35.3	2810	104
	APBR63X95A	Motor only	DC brush motor	12 - 115 V	63	15	3300	52
	APBR63X95B	Motor only	DC brush motor	12 - 115 V	63	20	4000	84
	APBR63X95C	Motor only	DC brush motor	12 - 115 V	63	20	9500	99
	APBR63X110A	Motor only	DC brush motor	12 - 115 V	63	31	3000	97
	APBR63X110B	Motor only	DC brush motor	12 - 115 V	63	35	4000	147
	APBR63X110C	Motor only	DC brush motor	12 - 115 V	63	40	7500	314
	APBR63X125A	Motor only	DC brush motor	12 - 115 V	63	40	3000	126

		Options de transmission	Type de moteur	Tension nominale U [V]	Diamètre moteur [mm]	Couple nominal [Ncm]	Vitesse nominale [U/min]	Puissance nominale [W]
	APBR63X125B	Motor only	DC brush motor	12 - 115 V	63	40	4000	167
	APBR76x98	Motor only	DC brush motor	12 - 230 V	76	30	2600	82
	APBR76x118	Motor only	DC brush motor	12 - 230 V	76	46	2600	125
	APBR76x138	Motor only	DC brush motor	12 - 230 V	76	65	2600	177
	APBR80x120	Motor only	DC brush motor	12 - 230 V	80	60	2900	182
	APBR80x140	Motor only	DC brush motor	12 - 230 V	80	80	2900	243
	APBR80x160	Motor only	DC brush motor	12 - 230 V	80	100	3000	314
	APBR90x155	Motor only	DC brush motor	12 - 230 V	90	120	3000	377

		Options de transmission	Type de moteur	Tension nominale U [V]	Diamètre moteur [mm]	Couple nominal [Ncm]	Vitesse nominale [U/min]	Puissance nominale [W]
	APBR90x199	Motor only	DC brush motor	12 - 230 V	90	180	3000	565
	APBL28x39	Motor only	BLDC-Motor	12 - 48 V	28	1	6000	7
	APBL28x49	Motor only	BLDC-Motor	12 - 48 V	28	1.5	6000	10
	APBL28x59	Motor only	BLDC-Motor	12 - 48 V	28	2	6000	15
	APBL36x45	Motor only	BLDC-Motor	12 - 48 V	36	3.6	4800	18
	APBL36x55	Motor only	BLDC-Motor	12 - 48 V	36	6	6000	40
	APBL36x65	Motor only	BLDC-Motor	12 - 48 V	36	7.5	8000	63
	APBL42x30	Motor only	BLDC-Motor	12 - 60 V	42	1.8	4000	7.6


		Options de transmission	Type de moteur	Tension nominale U [V]	Diamètre moteur [mm]	Couple nominal [Ncm]	Vitesse nominale [U/min]	Puissance nominale [W]
	APBL42x60	Motor only	BLDC-Motor	12 - 60 V	42	8	4000	33.5
	APBL42x85	Motor only	BLDC-Motor	12 - 60 V	42	15	4000	62
	APBL42x93	Motor only	BLDC-Motor	12 - 60 V	42	20	4000	85
	APBLS42x41	Motor only	BLDC-Motor	12 - 60 V	42	6.3	4000	26
	APBLS42x61	Motor only	BLDC-Motor	12 - 60 V	42	12.5	4000	52
	APBLS42x81	Motor only	BLDC-Motor	12 - 60 V	42	18.5	4000	77
	APBLS42x100	Motor only	BLDC-Motor	12 - 60 V	42	25	4000	104
	APBL(S)57x45	Motor only	BLDC-Motor	12 - 115 V	57	5.5	4000	23

		Options de transmission	Type de moteur	Tension nominale U [V]	Diamètre moteur [mm]	Couple nominal [Ncm]	Vitesse nominale [U/min]	Puissance nominale [W]
	APBL(S)57x55	Motor only	BLDC-Motor	12 - 115 V	57	11	4000	46
	APBL(S)57x75	Motor only	BLDC-Motor	12 - 115 V	57	22	4000	92
	APBL(S)57x95	Motor only	BLDC-Motor	12 - 115 V	57	32	4000	134
	APBL(S)57x115	Motor only	BLDC-Motor	12 - 115 V	57	42	4000	175
	APHBL(S)57x55	Motor only	BLDC-Motor	12 - 115 V	57	14	4000	58
	APHBL(S)57x75	Motor only	BLDC-Motor	12 - 115 V	57	28	4000	117
	APHBL(S)57x95	Motor only	BLDC-Motor	12 - 115 V	57	43	4000	180
	APHBL(S)57x115	Motor only	BLDC-Motor	12 - 115 V	57	49	4000	205

		Options de transmission	Type de moteur	Tension nominale U [V]	Diamètre moteur [mm]	Couple nominal [Ncm]	Vitesse nominale [U/min]	Puissance nominale [W]
	APBL60x78	Motor only	BLDC-Motor	12 - 60 V	60	30	3000	94
	APBL60x99	Motor only	BLDC-Motor	12 - 60 V	60	60	3000	188
	APBL60x120	Motor only	BLDC-Motor	12 - 60 V	60	100	3000	315
	APBLS70x86	Motor only	BLDC-Motor	12 - 60 V	70	50	3000	157
	APBLS70x116	Motor only	BLDC-Motor	12 - 60 V	70	100	3000	314
	APBLS70x136	Motor only	BLDC-Motor	12 - 60 V	70	150	3000	471
	APBLS80x85	Motor only	BLDC-Motor	12 - 230 V	80	30	3000	94
	APBLS80x105	Motor only	BLDC-Motor	12 - 230 V	80	65	3000	200



		Options de transmission	Type de moteur	Tension nominale U [V]	Diamètre moteur [mm]	Couple nominal [Ncm]	Vitesse nominale [U/min]	Puissance nominale [W]
	APBLS80x115	Motor only	BLDC-Motor	12 - 230 V	80	100	3000	315
	APBLS80x145	Motor only	BLDC-Motor	12 - 230 V	80	130	3000	410
	APBL80x60	Motor only	BLDC-Motor	12 - 230 V	80	40	3000	126
	APBL80x80	Motor only	BLDC-Motor	12 - 230 V	80	80	3000	252
	APBL80x100	Motor only	BLDC-Motor	12 - 230 V	80	120	3000	378
	APBL80x115	Motor only	BLDC-Motor	12 - 230 V	80	140	3000	442
	APBL80x135	Motor only	BLDC-Motor	12 - 230 V	80	180	3000	568
	APBLS86x80	Motor only	BLDC-Motor	12 - 230 V	86	100	3000	314





		Options de transmission	Type de moteur	Tension nominale U [V]	Diamètre moteur [mm]	Couple nominal [Ncm]	Vitesse nominale [U/min]	Puissance nominale [W]
	APBLS86x105	Motor only	BLDC-Motor	12 - 230 V	86	180	3000	565
	APBLS86x130	Motor only	BLDC-Motor	12 - 230 V	86	250	3000	785
	APBL86x80	Motor only	BLDC-Motor	12 - 230 V	86	100	3000	314
	APBL86x105	Motor only	BLDC-Motor	12 - 230 V	86	180	3000	565
	APBL86x130	Motor only	BLDC-Motor	12 - 230 V	86	250	3000	785
	APBLS110x93	Motor only	BLDC-Motor	12 -300 V	110	165	2830	440
	APBLS110x123	Motor only	BLDC-Motor	12 -300 V	110	330	2830	875
	APBLS110x153	Motor only	BLDC-Motor	12 -300 V	110	500	2370	1240

		Options de transmission	Type de moteur	Tension nominale U [V]	Diamètre moteur [mm]	Couple nominal [Ncm]	Vitesse nominale [U/min]	Puissance nominale [W]
	APBLS110x183	Motor only	BLDC-Motor	12 -300 V	110	660	2530	1750
	100.751-FC right	Worm gear	DC brush motor	24 V	77	700	191	140
	101.710-FC right	Worm gear	DC brush motor	24 V	77	1050	41	45
	102.698-FC left	Worm gear	DC brush motor	24 V	63	550	43	25
	100.650-FC right	Worm gear	DC brush motor	24 V	63	550	43	25
	100.657-FC left	Worm gear	DC brush motor	24 V	63	500	86	45
	100.667-FC left	Worm gear	DC brush motor	24 V	63	100	334	35
	100.676-FC right	Worm gear	DC brush motor	24 V	63	130	184	25

		Options de transmission	Type de moteur	Tension nominale U [V]	Diamètre moteur [mm]	Couple nominal [Ncm]	Vitesse nominale [U/min]	Puissance nominale [W]
	100.678-FC right	Worm gear	DC brush motor	24 V	63	1000	24	25
	100.686-FC right	Worm gear	DC brush motor	24 V	63	250	115	30
	101.634-FC right	Worm gear	DC brush motor	24 V	63	300	64	20
	101.690-FC left	Worm gear	DC brush motor	24 V	63	150	255	40
	101.649-FC right	Worm gear	DC brush motor	24 V	63	900	42	40
	102.643-FC left	Worm gear	DC brush motor	24 V	63	500	105	55
	100.604-FC left	Worm gear	DC brush motor	24 V	63	200	119	25
	103.607-FC left	Worm gear	DC brush motor	24 V	63	200	215	45

		Options de transmission	Type de moteur	Tension nominale U [V]	Diamètre moteur [mm]	Couple nominal [Ncm]	Vitesse nominale [U/min]	Puissance nominale [W]
	100.652-FC left	Worm gear	DC brush motor	24 V	63	1000	24	25
	100.656-FC right	Worm gear	DC brush motor	24 V	63	600	8	5
	103.636-FC left	Worm gear	DC brush motor	12 V	63	150	223	35
	103.694-FCE left	Worm gear	DC brush motor	24 V	63	1000	38	40
	104.629-FCE right	Worm gear	DC brush motor	24 V	63	150	191	30
	104.641-FC left	Worm gear	DC brush motor	24 V	63	100	286	30
	106.626-FC right	Worm gear	DC brush motor	24 V	63	150	255	40
	105.695-FC left	Worm gear	DC brush motor	24 V	63	320	90	30

		Options de transmission	Type de moteur	Tension nominale U [V]	Diamètre moteur [mm]	Couple nominal [Ncm]	Vitesse nominale [U/min]	Puissance nominale [W]
	102.728-FC left	Worm gear	DC brush motor	24 V	77	1050	18	20
	101.710-FCEE right	Worm gear	DC brush motor	24 V	77	1050	41	45
	102.736-FC right	Worm gear	DC brush motor	12 V	77	100	458	48
	105.695-12-FC left	Worm gear	DC brush motor	12 V	59	2700	8	22
	107.631-FC left	Worm gear	DC brush motor	24 V	59	350	123	45
	107.651-FC right	Worm gear	DC brush motor	24 V	63	1000	24	25
	107.698-FC left	Worm gear	DC brush motor	24 V	63	400	131	55
	105.632-FC right	Worm gear	DC brush motor	24 V	63	150	255	40

		Options de transmission	Type de moteur	Tension nominale U [V]	Diamètre moteur [mm]	Couple nominal [Ncm]	Vitesse nominale [U/min]	Puissance nominale [W]
	102.766-FC left	Worm gear	DC brush motor	42 V	77	600	175	110
	100.695-FC right	Worm gear	DC brush motor	24 V	63	130	184	25
	102.718-FC right	Worm gear	DC brush motor	12 V	77	200	346	72.5
	107.691-FCEE left	Worm gear	DC brush motor	24 V	63	100	525	55
	103.739-FC right	Worm gear	DC brush motor	24 V	77	650	29	20
	103.748-FCEE left	Worm gear	DC brush motor	24 V	77	1050	41	45

We are here for you. Addresses and Contacts.

Headquarter Switzerland:

Angst+Pfister Sensors and Power AG
Thurgauerstrasse 66
CH-8050 Zurich
Phone +41 44 877 35 00
sensorsandpower@angst-pfister.com

Office Germany:

Angst+Pfister Sensors and Power Deutschland GmbH
Edisonstraße 16
D-85716 Unterschleißheim
Phone +49 89 374 288 87 00
sensorsandpower.de@angst-pfister.com

Scan here and get an overview of personal contacts!



sensorsandpower.angst-pfister.com