



|                                                                                    |              | Plage de mesure               | Type de pression            | Tension d'alimentation | Signal de sortie                                              | Précision [%] | Plage de temp. [°C] |
|------------------------------------------------------------------------------------|--------------|-------------------------------|-----------------------------|------------------------|---------------------------------------------------------------|---------------|---------------------|
|    | 85           | 0 to 2.5 mbar...7 bar         | Gauge, Vacuum, Differential | 3.0, 3.3, 5, Custom    | 0...1 V, 0.2...4.5 V, 0.5...4.5 V, 4...20mA, I2C, SPI, Custom | 0.5 FS        | -20 to +85°C        |
|    | 86           | 0 to 100 mbar...50 bar        | Gauge, Absolute             | 3.3V, 5V               | 0.5...4.5 V, 0.2...4.7 V, I2C, Custom                         | 1 FS          | -20 to +85°C        |
|    | PEWA100      | -1...0 / 0 to 0.35...1000 bar | Gauge, Vacuum, Absolute     | 5VDC / 12...30VDC      | 0...10 V/4...20 mA, 0/1...5 VDC; 0.5...4.5 VDC ratiometrisch  | 0.5 FS        | -30 to 105          |
|    | PEWA200      | -1...0 / 0 to 0.35...1000 bar | Gauge, Vacuum, Absolute     | 5VDC / 12...30VDC      | 0...10 V/4...20 mA, 0/1...5 VDC; 0.5...4.5 VDC ratiometrisch  | 0.5 FS        | -30 to 105          |
|    | PEWA370H H2  | 0 to 0.25...70 bar            | Gauge, Absolute             | 5VDC / 3.2...28VDC     | 0...10 V/4...20 mA, 0/1...5 VDC; 0.5...4.5 VDC ratiometrisch  | 0.25 FS       | -30 to 85           |
|   | PEWA3411H H2 | 0 to 16...1000 bar            | Gauge                       | 5VDC / 5...33VDC       | 0...10 V/4...20 mA, 0/1...5 VDC; 0.5...4.5 VDC ratiometrisch  | 0.5 FS        | -40 to 125          |
|  | PEWA1099     | 0 to 2...10 bar               | Differential                | 18...30 VAC/VDC        | 0...10 V/4...20 mA                                            | 1.5 FS/1 FS   | -20 to +85          |
|  | PEWA3403     | 0 to 3...50 bar               | Gauge                       | 3.3...28VDC            | 0.5...4.5 V, I2C                                              | 1 FS          | 0 to 70             |

|                                                                                    |                                       | Plage de mesure                                                                 | Type de pression            | Tension d'alimentation | Signal de sortie                                             | Précision [%] | Plage de temp. [°C] |
|------------------------------------------------------------------------------------|---------------------------------------|---------------------------------------------------------------------------------|-----------------------------|------------------------|--------------------------------------------------------------|---------------|---------------------|
|    | <b>PHPS-5500</b>                      | 0 to 20 mbar...7 bar                                                            | Gauge                       | 7...40V                | Analog, Digital M8                                           | 0.5 FS        | 0 - 70              |
|    | <b>PHPS-5600</b>                      | 0 to 20 mbar...7 bar                                                            | Gauge                       | 7...40V                | Analog, Digital M8                                           | 0.5 FS        | 0°C to 70           |
|    | <b>981</b>                            | 0 to 100 mbar.                                                                  | Gauge                       | 24 VDC                 | 0...10 V/4...20 mA                                           | < 1 FS        | -20 to 85           |
|    | <b>985Q</b>                           | 0 to 50 Pa...2500 Pa<br>(8 pressure ranges in one transmitter; set with jumper) | Gauge, Vacuum, Differential | 18...30 VAC/VDC        | 0...10 V/4...20 mA                                           | 1 FS          | 0 to 50             |
|    | <b>985V - Volume flow transmitter</b> | 0 to 50 Pa...10 kPa                                                             | Gauge, Vacuum, Differential | 22...30 VAC/VDC        | 0...10 V/4...20 mA                                           | 1 FS          | 0 to 50             |
|    | <b>PAMS3011 - PAMS3012</b>            | 0 to 25 mbar...10 bar                                                           | Gauge, Vacuum, Absolute     | 8...36 VDC             | 0...10 V/4...20 mA, 0...5 VDC                                | 0.5 FS        | -25 to 85           |
|  | <b>PAMS4711 - PAMS4712</b>            | 0 to 5 mbar...2 bar                                                             | Gauge, Vacuum, Absolute     | 8...36 VDC             | 0...10 V/4...20 mA, 0...5 VDC                                | 0.5 FS        | -25 to 85           |
|  | <b>Pirani 80A</b>                     | 10E-3 Torr (Vacuum)                                                             | Vacuum                      | 9...32 VDC             | 0...10 V/4...20 mA, 0/1...5 VDC; 0.5...4.5 VDC ratiometrisch | 0.5 FS        | -40 to 125          |

|                                                                                    |             | Plage de mesure      | Type de pression            | Tension d'alimentation | Signal de sortie   | Précision [%] | Plage de temp. [°C] |
|------------------------------------------------------------------------------------|-------------|----------------------|-----------------------------|------------------------|--------------------|---------------|---------------------|
|    | <b>982R</b> | 0 to 50 Pa...100 kPa | Gauge, Vacuum, Differential | 18...30 VAC/VDC        | 0...10 V/4...20 mA | 1 FS          | 0 to 50             |
|    | <b>984M</b> | 0 to 50 Pa...100 kPa | Gauge, Vacuum, Differential | 18...30 VAC/VDC        | 0...10 V/4...20 mA | 1 FS          | 0 to 50             |
|    | <b>984A</b> | 0 to 25 Pa...100 kPa | Gauge, Vacuum, Differential | 22...30 VAC/VDC        | 0...10 V/4...20 mA | 1 FS          | 0 to 50             |
|    | <b>985M</b> | 0 to 50 Pa...100 kPa | Gauge, Vacuum, Differential | 22...30 VAC/VDC        | 0...10 V/4...20 mA | 1 FS          | 0 to 50             |
|    | <b>985A</b> | 0 to 25 Pa...100 kPa | Gauge, Vacuum, Differential | 22...30 VAC/VDC        | 0...10 V/4...20 mA | 1 FS          | 0 to 50             |
|    | <b>990M</b> | 0 to 25 Pa...250 kPa | Gauge, Vacuum, Differential | 18...30 VAC/VDC        | 0...10 V/4...20 mA | 1 FS          | 0 to 50             |
|  | <b>990A</b> | 0 to 25 Pa...250 kPa | Gauge, Vacuum, Differential | 22...30 VAC/VDC        | 0...10 V/4...20 mA | 1 FS          | 0 to 50             |

## We are here for you. Addresses and Contacts.

---

### Headquarter Switzerland:

Angst+Pfister Sensors and Power AG  
Thurgauerstrasse 66  
CH-8050 Zurich  
Phone +41 44 877 35 00  
[sensorsandpower@angst-pfister.com](mailto:sensorsandpower@angst-pfister.com)

### Office Germany:

Angst+Pfister Sensors and Power Deutschland GmbH  
Edisonstraße 16  
D-85716 Unterschleißheim  
Phone +49 89 374 288 87 00  
[sensorsandpower.de@angst-pfister.com](mailto:sensorsandpower.de@angst-pfister.com)

Scan here and get an overview of personal contacts!



[sensorsandpower.angst-pfister.com](https://sensorsandpower.angst-pfister.com)